Series 3300 Conventional Manual Pull Stations



K-84-08 Effective: August 2021

FEATURES

- Unique Field Labeling for either Fire Alarm or Suppression Applications
- Dual Action Operation
- Single Pole or Double Pole
- Keylock for Reset
- FM Approved
- cULus Listed for US and Canada
- Surface and Weatherproof Backboxes
- Backwards compatible mounting with Model B-10 and B-11 Pull Stations

DESCRIPTION

The Kidde[®] Conventional SPST and DPST Series 3300 Manual Pull Stations are high quality, non-coded alarm initiating devices. The Manual Pull Stations are constructed of heavy die-cast aluminum for long life and use an internal toggle switch for reliable operation.

The SPST Manual Pull Station provides an Single Pole, Single Throw switch with screw terminal connections for wiring to the fire alarm/suppression control unit.

The DPST Manual Pull Station provides a Dual Pole, Single Throw switch with screw terminal connections. One set of contacts must be wired to the fire alarm/suppression control unit and the other may be used for local or remote annunciation.

These Manual Pull Stations are designed for quick, efficient response by personnel in an emergency, while the double action PUSH/PULL levers prevent accidental operation. This unit should use a break rod as an indicator of operation.

The Manual Pull Stations can be mounted in an indoor or outdoor weatherproof backbox (Model SBG-32S or Model SGB-32C) or a North American 2-1/2 in. (64 mm) deep 1-gang box. The Manual Pull Station terminal block accepts 14, 16 and 18 AWG wire.

FIRE ALARM OR SUPPRESSION RELEASE LABELING

The Kidde Series 3300 Manual Pull Stations have a unique labeling method which provides the installer the greatest amount of flexibility. Seven labels are shipped with each station:

- FIRE ALARM
- FM-200 RELEASE
- CO₂ RELEASE
- FE-13 RELEASE
- FIRE SYSTEMS RELEASE

NOVEC 1230 RELEASE

- HALON-1301 RELEASE
- RELEASE



These permanent, heavy-duty Lexan[®] self-adhesive labels are die-cut with raised lettering. During installation, the installer simply chooses the appropriate label, removes the protective backing, and places the label into the space on the top of the station. This flexibility allows installations to be customized for each customer, without the expense of having to carry extra inventory.

OPERATION

The dual action Series 3300 manual stations are operated by simply pushing the PUSH bar inwards, allowing the PULL handle to be grasped in a one-handed motion. The handle is then pulled down as far as it will go. If the optional breakrod is installed, it would break at this point. The handle is now locked in place, and is easily visible from up to 50 feet away. The handle is reset by opening the station with the key and placing the handle in the normal upright position. Place the switch actuator in the down position, insert breakrod into cavity beneath handle (if applicable), and re-lock the station.

SPECIFICATIONS

Station Type: Double Action, Non-coded

Switch Type: P/N 84-330001-001: SPST

P/N 84-330001-002: DPST

Switch rating: 2 Amp @ 240 Vac or 125 Vdc

Operating Tempera-

ture Range:

-40°F to 150°F (-40°C to 66°C)

Operating Humidity

Range:

0-95% RH

Construction: Die-cast metal housing

Compatible Electrical

Boxes:

Indoor: Sheet metal Model SGB-Outdoor: Weatherproof Die-cast

Model SGB-32C

Shipping Weight: 1.12 lbs. (510 g)

SGB-32S INTERIOR SURFACE BACKBOX

Dimensions: 4.75 in. H x 3.25 in. W x 2.25 in. D

Construction: Steel sheet metal.

Conduit: Two knockouts for 1/2 in. conduit

connectors, one on top and bottom.

Mounting: Mounts to the box with (4) 8/32

screws, which ship with each box.

SGB-32C WEATHERPROOF SURFACE **BACKBOX**

Dimensions: 4.75 in. H x 3.25 in. W x 2.25 in. D

Construction: Cast aluminum.

Conduit: One threaded opening for 3/4 in.

conduit connector.

Mounting: Mounts to the box with (4) 8/32

screws and a foam gasket, which


ship with each box.

ORDERING INFORMATION

Part Number	Description
84-330001-001	Dual Action Manual Pull Station with SPST Switch — ships with mounting hardware, 2 keys, 1 break rod, and label set.
84-330001-002	Dual Action Manual Pull Station with DPST Switch — ships with mounting hardware, 2 keys, 1 break rod, and label set.
84-100009-001	SGB-32S Indoor Backbox
84-100009-002	SGB-32C Outdoor Waterproof Backbox
84-100008-002	Pkg. of (12) Breakrods
06-118013-001	Spare Key
06-231866-930	Label Set

DIMENSIONS

(shown with Fire System Release Label installed)



EXPORT INFORMATION (USA)

Jurisdiction: EAŔ US ECCN: EAR99

This document contains technical data subject to the EAR.

Kidde is a registered trademark of Kidde-Fenwal, Inc., or its parents, subsidiaries or affiliates. Lexan is a trademark of SABIC.

This literature is provided for informational purposes only. KIDDE-FENWAL, INC. believes this data to be accurate, but it is published and presented without any quarantee or warranty whatsoever. KIDDE-FENWAL, INC. assumes no responsibility for the product's suitability for a particular application. Product features specified are only applicable when the fire suppression system is correctly designed, installed, maintained and serviced by trained, authorized Kidde Fire Systems distributors as per the applicable design, installation, operation, and maintenance manuals. If you need more information on this product, or if you have a particular problem or question, contact: KIDDE-FENWAL, INC., Ashland, MA 01721 USA, Telephone: (508) 881-2000.

